

Technical Specifications

APC Back-UPS 1000VA Without Battery with Selectable Charger and Flooded/SMF compatible, 230V, India | BX1000UXI | Downloaded on 01/02/2021 (EST)



APC Back-UPS 1000VA Without Battery with Selectable Charger and Flooded/SMF compatible, 230V, India

BX1000UXI

Call for More Information 18001030011

- Includes: User manual, Warranty card

Output

Output power capacity	600 Watts / 1.0kVA
Max Configurable Power (Watts)	600 Watts / 1.0kVA
Nominal Output Voltage	230V
Efficiency at Full Load	92.0 %
Output Frequency (sync to mains)	50 Hz +/- 1 Hz Unsynchronised
Topology	Square
Waveform type	Stepped approximation to a sinewave
Output Connections	(4) India 2/3-pin 6A
Transfer Time	8 ms typical : 12 ms maximum

Input

Nominal Input Voltage	230V
Input frequency	40 - 70 Hz
Input Connections	India 3-pin 6A
Cord Length	0.5meters
Efficiency at Full Load	92.0 %

Batteries & Runtime

Battery type	External battery system
--------------	-------------------------

Communications & Management

Control panel	LED Status display with on line : on battery
---------------	--

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.

Technical Specifications

APC Back-UPS 1000VA Without Battery with Selectable Charger and Flooded/SMF compatible, 230V, India | BX1000UXI | Downloaded on 01/02/2021 (EST)

Physical	
Maximum Height	220MM, 22.0CM
Maximum Width	145MM, 14.5CM
Maximum Depth	392MM, 39.2CM
Net Weight	9.3KG
Shipping weight	10.2KG
Shipping Height	335MM, 33.5CM
Shipping Width	235MM, 23.5CM
Shipping Depth	477MM, 47.7CM
Master Carton Weight	0.7
Pallet Dimensions	47.24 x 39.37 x 4.96inches
Pallet Weight	41.89lbs.

Environmental	
Operating Temperature	0 - 40 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0 - 914.4meters
Storage Temperature	0 - 45 °C
Storage Elevation	0 - 3048meters
Audible noise at 1 meter from surface of unit	50.0dBA

Conformance	
Standard warranty	2 years repair or replace

Sustainable Offer Status	
RoHS	Compliant

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.