



APC Smart-UPS 750VA USB & Serial 230V, India Specific

SUA750I-IND

Call for More Information 18001030011

 Includes: CD with software, Smart UPS signalling RS-232 cable, USB cable, User manual

Output	
Output power capacity	500 Watts / 750VA
Max Configurable Power (Watts)	500 Watts / 750VA
Nominal Output Voltage	230V
Output Voltage Note	Configurable for 220 : 230 or 240 nominal output voltage
Output Voltage Distortion	Less than 5 %
Output Frequency (sync to mains)	47 - 53 Hz For 50 Hz nominal Sync to mains
Topology	Line interactive
Waveform type	Sine wave
Output Connections	(4) India 3-pin 6A
Transfer Time	2 ms typical

Input	
Nominal Input Voltage	230V
Input frequency	50/60 Hz +/- 3 Hz Auto-sensing
Input Connections	IEC 60320 C14
Input voltage range for main operations	151 - 302 Adjustable, 160 - 282V

Batteries & Runtime	
Battery type	Lead-acid battery
Typical recharge time	4hour(s)
Efficiency	View Efficiency Graph (Available in Technical Tab on site)

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.



Communications & Management	
Interface Port(s)	DB-9 RS-232, SmartSlot, USB
Control panel	LED status display with on line : on battery : replace battery and overload indicators
Audible Alarm	Alarm when on battery : distinctive low battery alarm : configurable delays

Physical	
Maximum Height	157MM, 15.7CM
Maximum Width	137MM, 13.7CM
Maximum Depth	361MM, 36.1CM
Net Weight	13.15KG
Shipping weight	14.55KG
Shipping Height	290MM, 29.0CM
Shipping Width	270MM, 27.0CM
Shipping Depth	500MM, 50.0CM
Units per Pallet	24.0

Environmental	
Operating Temperature	0 - 40 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0 - 3048meters
Storage Temperature	-15 - 45 °C
Storage Elevation	0 - 15240meters
Audible noise at 1 meter from surface of 41.0dBA unit	

Conformance	
Approvals	BIS
Standard warranty	2 years repair or replace

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.